

LUXA-31 (3-IN-1)

socket | white | integrated 24 V driver with switch

Product code: 631224



Dual socket with integrated 24 V LED power supply and switch (2-in-1)

The LIMENTE LUXA-31 is a corner socket that includes a power supply for LED lights and an on/off switch to control the kitchen work space lights. It is quick and easy to install and can be used with all types of LIMENTE LED lights. The tilted design makes the sockets easy to access and you can clearly see in which direction the plug should be inserted. The material is either stainless steel, painted white or black (metal body). The sockets are child proof and designed in Finland.

LUXA sockets have two plug places, 30w power supply and an on/off switch for led-lights. The switch allows you to control for example kitchen work lights. By combining LIMENTE LUXA with LIMENTE profile lights, you will create a stylish combination for your kitchen. The design of the LIMENTE LUXA is similar to LIMENTE MINI sockets, so you can elegantly combine these models in the same kitchen. With the LIMENTE LUXA you can easily replace the traditional fluorescent lamp + socket combination with the modern LED lighting without any major electrical installations. LIMENTE LUXA is installed in place of the fluorescent lamp and the LUXA socket replaces the socket and light switch. In addition, you need any 24 V LIMENTE lights that you connect to the 24V power supply that is inted in the LUXA socket. These lights are controlled by the switch on the socket.

[Learn more from our website](#)

Socket color options

The Luxa socket is available in white, stainless steel and black. Stainless steel is brushed and both white and black have a matte finish (matte black and matte white). All color options have a sturdy metal body.

Installation and electrical connection

Specify the location where the power cord will be imported, or use an existing power cord. The power cord is plugged in from the wall. The socket is mounted at an angle against two solid, non-flammable surfaces so that its background does not remain open. The actual fastening is done with the help of the included screws. In one installation, you install both the sockets, the switch and power supply for the LED lights. See the installation instructions for more detailed instructions.

[Learn more from our website](#)

THE FOLLOWING ITEMS ARE INCLUDED

- double socket
- back plate
- integrated 30W driver controlled by an integrated switch
- 2 x driver for LED luminaires female with TOP connectors
- quick connector for connection
- plastic free packaging

LUXA-31 SOCKET WITH DRIVER WH

OVERVIEW

PRODUCT CODE	631224
GTIN-CODE	6438400002937
ELECTRICAL NUMBER	2407134
ETIM GENERAL NAME	Socket outlet+switch
ETIM CLASS	Socket outlet EC000125
ETIM GROUP	24 Surface mounting socket-outlets and plugs
COLOUR	
LAMP TYPE	

SPECIFICATIONS

PRODUCT DIMENSIONS	214.0 x 175.0 x 58.0
MOUNTING METHOD	Surface mounting, Fixed installation
COLOUR TEMPERATURE	
COLOUR RENDERING INDEX CRI	
RATED LIFE TIME	
ENERGY EFFICIENCY CLASS	
LUMINOUS FLUX	
EFFICIENCY	
VOLTAGE	240 V, 24 V DC
INGRESS PROTECTION CODE	IP20
NUMBER OF LEDS/M	
INPUT POWER	
NUMBER OF SWITCHING CYCLES	
AMBIENT TEMPERATURE RANGE	-20°C +- 50°C
INPUT POWER CONNECTOR	Fixed installation
WARRANTY PERIOD (MONTHS)	24
ADDITIONAL COVER (MONTHS)	
INSTALLATION AND OPERATING MANUAL	

LUXA-31 SOCKET WITH DRIVER WH

RECOMMENDED ACCESSORIES

PRODUCT CODE	PRODUCT
631221	LUXA-31 (3-IN-1), SOCKET, STAINLESS STEEL, INTEGRATED 24 V DRIVER WITH SWITCH
631229	LUXA-31 (3-IN-1), SOCKET, BLACK, INTEGRATED 24 V DRIVER WITH SWITCH
631239	LUXA-32 (4-IN-1), SOCKET, BLACK, INTEGRATED 24 V DRIVER, DOUBLE SWITCH
631234	LUXA-32 (4-IN-1), SOCKET, WHITE, INTEGRATED 24 V DRIVER, DOUBLE SWITCH
631231	LUXA-32 (4-IN-1), SOCKET, STAINLESS STEEL, INTEGRATED 24 V DRIVER, DOUBLE SWITCH
631581	LUNA-2, STAINLESS STEEL, INCL. SWITCH
631584	LUNA-2, WHITE, INCL. SWITCH
631589	LUNA-2, BLACK, INCL. SWITCH

LUXA-31 SOCKET WITH DRIVER WH

