

TURN

socket |

Product code: 63184



Electrically pop-up socket

The stylish socket embedded in the surface turns out spectacularly when you place your finger on the blue light in the socket. The four sockets installed in the frame are now ready to use. After use you can close the socket by placing your finger on the blue light again. The blue light of the socket always lights up when the socket is in place, and during turning the light turns red and flashes. When closed, the sockets are hidden and the high-quality finished flat surface and the small side sensors are visible.

[Learn more from our website](#)

Color options

VersaTurn always has a surface material in stainless steel.

Installation

VersaTurn socket is easy and quick to install. A hole is made in the tabletop (10 - 55 mm) according to the installation instructions, where the socket is placed and tightened from below with the included tightening screws. The electrical connection is made with the supplied 2 m plug-in cable. Note that there must be a grounded outlet at a distance of max. two meters and that the outlet requires an installation depth of approx. 10 cm.

THE FOLLOWING ITEMS ARE INCLUDED

- socket with 2m supply cable
- grounded plug

TURN SOCKET WHITE

OVERVIEW

PRODUCT CODE	63184
GTIN-CODE	8028067029897
ELECTRICAL NUMBER	2529509
ETIM GENERAL NAME	Socket
ETIM CLASS	Socket outlet EC000125
ETIM GROUP	25 Flush sockets
COLOUR	
LAMP TYPE	

SPECIFICATIONS

PRODUCT DIMENSIONS	390.0 x 112.0 x 102.0
MOUNTING METHOD	Flush mounting
COLOUR TEMPERATURE	
COLOUR RENDERING INDEX CRI	
RATED LIFE TIME	
ENERGY EFFICIENCY CLASS	
LUMINOUS FLUX	
EFFICIENCY	
VOLTAGE	240 V
INGRESS PROTECTION CODE	IP20
NUMBER OF LEDS/M	
INPUT POWER	
NUMBER OF SWITCHING CYCLES	
AMBIENT TEMPERATURE RANGE	5°C~40°C
INPUT POWER CONNECTOR	
WARRANTY PERIOD (MONTHS)	24
ADDITIONAL COVER (MONTHS)	
INSTALLATION AND OPERATING MANUAL	http://www.limente.fi/Images/productpics/instructions/Limente_Turn.pdf