

RIM-21

white | 21 W | 1910 lm

Product code: 611984



An inexpensive extendable fluorescent light fixture

LIMENTE RIM light fixtures can be used anywhere a small, inexpensive and inconspicuous light fixture is needed. Three standard lengths are available: 612mm (14W), 912mm (21W) and 1205mm (28W). Each fixture has an integrated light switch.

Due to its small size, LIMENTE RIM is easy to hide and use for example as indirect light above a cabinet or as working light behind a light board. The fixture includes a switch, power cords (both for power supply and extensions) and attachment brackets for both wall- and ceiling-mounting. The power cord for extensions has connectors at both ends and a length of 24cm (cord 13cm + connectors).

[Learn more from our website](#)

Dimming and lighting control

LIMENTE RIM is not dimmable.

Installation

LIMENTE RIM is installed with the supplied installation tools and brackets either downward or horizontal. Either way, the fixture projects light in all directions.



THE FOLLOWING ITEMS ARE INCLUDED

- fluorescent lamp
- switch
- power cord
- intermediate cable
- wall and roof fasteners

RIM-21 FLUORESCENT LIGHT

OVERVIEW

PRODUCT CODE	611984
GTIN-CODE	6430022826403
ELECTRICAL NUMBER	4118803
ETIM GENERAL NAME	Work point luminaire
ETIM CLASS	Batten luminaire EC000109
ETIM GROUP	41 Domestic light fittings
COLOUR	White
LAMP TYPE	Flourescence tube

SPECIFICATIONS

PRODUCT DIMENSIONS	912.0 x 42.0 x 22.0
MOUNTING METHOD	Surface mounting
COLOUR TEMPERATURE	4000 K
COLOUR RENDERING INDEX CRI	> 80
RATED LIFE TIME	15.000 h
ENERGY EFFICIENCY CLASS	
LUMINOUS FLUX	1910 lm
EFFICIENCY	91 lm/W
VOLTAGE	240 V
INGRESS PROTECTION CODE	IP20
NUMBER OF LEDS/M	
INPUT POWER	21 W
NUMBER OF SWITCHING CYCLES	> 50 000
AMBIENT TEMPERATURE RANGE	
INPUT POWER CONNECTOR	Europlug
WARRANTY PERIOD (MONTHS)	24
ADDITIONAL COVER (MONTHS)	-
INSTALLATION AND OPERATING MANUAL	http://www.lapetek.fi/tuotekuvat/ao/lapetek_rim.pdf

RIM-21 FLUORESCENT LIGHT

