

LIMENTE EXTENSION CABLE

2 m | white | 24 V

Product code: 681550



LIMENTE IR-PIR SENSOR Extension cord

With the 2-meter extension cable for LIMENTE SMART IR-PIR sensors, you can install your detector exactly where you need it most.

The extension cable allows you to position the IR and PIR detectors significantly further away from the electronics unit than the included 2-meter cable permits. By connecting this 2-meter extension cable between the IR or PIR sensor and the standard cable, you can install the sensor up to 4 meters away from the electronics unit. (Standard 2 m cable + 2 m extension cable = 4 m total length).

[Learn more from our website](#)

THE FOLLOWING ITEMS ARE INCLUDED

- 2 m led-extension cord for SMART IR/PIR sensors
- Plastic Free packaging

EXTENS. CABLE 2M IR-PIR SENSOR

OVERVIEW

PRODUCT CODE	681550
GTIN-CODE	6430022827059
ELECTRICAL NUMBER	4009759
ETIM GENERAL NAME	
ETIM CLASS	
ETIM GROUP	
COLOUR	
LAMP TYPE	

SPECIFICATIONS

PRODUCT DIMENSIONS	2000.0 x 8.2 x 8.2
MOUNTING METHOD	
COLOUR TEMPERATURE	
COLOUR RENDERING INDEX CRI	
RATED LIFE TIME	
ENERGY EFFICIENCY CLASS	
LUMINOUS FLUX	
EFFICIENCY	
VOLTAGE	
INGRESS PROTECTION CODE	
NUMBER OF LEDS/M	
INPUT POWER	
NUMBER OF SWITCHING CYCLES	
AMBIENT TEMPERATURE RANGE	
INPUT POWER CONNECTOR	
WARRANTY PERIOD (MONTHS)	
ADDITIONAL COVER (MONTHS)	
INSTALLATION AND OPERATING MANUAL	

EXTENS. CABLE 2M IR-PIR SENSOR

